

**D3**


User manual of products

Read this instruction carefully before using the product

Introduction to FiiO D3—Optical/Coaxial R/L Analog convertor

① Digital signal coaxial input port**② Coaxial/Optical switch:**Put it upward is coaxial ,Downward is optical **③ Digital signal optical input port****④ Analog audio signal RCA L/R output port****⑤ USB power supply input: DC5V****⑥ Indicated light for signal status:**

when machine work, the blue light on.

⑦ Power indicator: when power on, red light is on; power off, the light off.**List of items in the package (please verify)**

D3	1PCS
Power adaptor	1PCS
User manual	1PCS

D3 BRIEF INSTRUCTION

D3 is a digital audio analog convertor, which can transfer digital audio (optical/coaxial) to two channels analog audio and amplify the output (but using directly on headphone is not recommended), just suitable for using together with the devices such as digital television, CD/DVD/Blue-ray player etc., which with coaxial or optical digital signal output.

Feature and main function:

- Built-in high-performance phase locked loop (PLL), with extra-low JITTER digital receiver chip WM8805.
- Maximum support 192KHz/24bit audio signal
- Optical/coaxial optional input function
- 2 channels standard RCA output port
- Indication for digital receiving status (LOCKED)
- MINI USB power supply port

Specifications:

Power supply	DC 5V
Output amplitude	1.6V (0dB Fs)
Frequency Response	20Hz~20KHz
Signal to Noise Ratio	≥90dB
Crosstalk	75dB
Total harmonic distortion	<0.01%(10mW)
Size	61.6mm×49.1mm×21mm
Weight	50g

IMPORTANT NOTICE

Important note:

- ★ Please keep the device dry and far away from moisture and humid environment, such as rain and any liquid or water with corrosion that will damage the device
- ★ Do not try to open, repair the device and place it near a source of liquid
- ★ Please see to it that original power supply are required, or high quality power supply with voltage range with 5V=200mA, with out warranty when the device be damaged by the third party using unsuitable power supply
- ★ If the native machine cannot work normally or any other questions, please visit our website (<http://www.fii.com.cn/support/FeekBack.aspx>) to post comments or send email to service@fii.com.cn

Cannot work or abnormal to work :

- with no sound output or with distortion, please be sure that the audio source and music file is not damaged, or try to re-plug the USB power
- Music input connector might have a faulty or unsuitable connection, please reconnect the plug
- Please use the include stock cable or a compatible frequency connect cable in order to ensure a secured output

Qualified Certificate

V01

DATE:
(D-M-Y)

Guangzhou FiiO Electronic Technology LTD
 Tel:86-20-62679040 Fax:86-20-62679042
 Address: 2/F, F Building, Hougang Industrial Zone, Shigang Village,
 Huangshi West Road, Baiyun District, Guangzhou City, China.
 Website: www.fii.com.cn Postcode: 510430

5190075

Manufactured by FiiO

Made in China